

Functional Devices, Inc.


310 South Union Street Russiaville, IN 46979 www.FunctionalDevices.com Office 765.883.5538 Sales 800.888.5538 Fax 765.883.7505 Email sales@FunctionalDevices.com



Relay & Current Transducer Combo

US

RIBX243PV Enclosed Internal 0-20 Amp to 0-10 Vdc Current Transducer + Relay 20 Amp 3PST with 24 Vac/dc Coil



Coil Current: 210 mA @ 24 Vac 154 mA @ 30 Vdc Coil Voltage Input: 24 Vac/dc ; 50-60 Hz Drop Out = 3 Vac / 3.8 Vdc Pull In = 20 Vac / 20 Vdc

Sensor Type: Internal, with voltage output. Current sensing on orange wires Sensor Range: 0-20 Amps

Notes:

» Order Normally Closed by adding "-NC" to end of model number

» Can be ordered with 0-5 Vdc voltage output - Consult factory

SPECIFICATIONS

 # Relays & Contact Type: One (1) 3PST Continuous Duty Coil Expected Relay Life: 10 million cycles minimum mechanical Operating Temperature: -30 to 140° F Operate Time: 20mS Relay Status: Red LED On = Activated Dimensions: 4.00″ x 4.00″ x 1.80″ with .50″ NPT Nipple Wire Length: 16″, 600V Rated Approvals: UL Listed, UL916, UL864, C-UL California State Fire Marshal, CE, RoHS Housing Rating: Plenum, NEMA 1 Gold Flash: No

Contact Ratings:

20 Amp Resistive @ 300 Vac, 28 Vdc 20 Amp Resistive @ 300 Vac, 28 Vdc 20 Amp Ballast @ 277-480 Vac 15 Amp Resistive @ 600 Vac 770 VA Pilot Duty @ 120 Vac, 1 Phase 1158 VA Pilot Duty @ 240 Vac, 1 Phase 1168 VA Pilot Duty @ 240 Vac, 1 Phase 1460 VA Pilot Duty @ 240 Vac, 3 Phase 1466 VA Pilot Duty @ 480 Vac, 3 Phase 2112 VA Pilot Duty @ 480 Vac, 3 Phase 2112 VA Pilot Duty @ 600 Vac 7.5 HP @ 480 Vac, 3 Phase 5 HP @ 240 Vac, 3 Phase 3 HP @ 480-600 Vac, 1 Phase 2 HP @ 240 Vac, 1 Phase 1 HP @ 120 Vac, 1 Phase

Notes