



# Functional Devices, Inc.

310 South Union Street Russiaville, IN 46979 www.FunctionalDevices.com Office 765.883.5538 Sales 800,888,5538 Fax 765.883.7505


Email sales@FunctionalDevices.com



# 20 Amp Power Control Relays


### RIBT24B

Enclosed Relay Hi/Low Separation 20 Amp SPDT with 24 Vac/dc Coil



# **RIBT24SB**

Enclosed Relay Hi/Low Separation 20 Amp SPST + Override with 24 Vac/dc Coil



#### **■ SPECIFICATIONS**

# Relays & Contact Type: One (1) SPDT Continuous Duty Coil (RIBT24B) One (1) SPST Continuous Duty Coil (RIBT24SB)

Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: -30 to 140° F Operate Time: 18mS

Relay Status: LED On = Activated

**Dimensions:** 4.00" x 4.00" x 1.80" with .50" NPT Nipple

Wires: 16", 600V Rated

Approvals: UL Listed, UL916, UL864, C-UL California State Fire Marshal, CE, RoHS

Housing Rating: Plenum, NEMA 1

Gold Flash: No

Override Switch: No (RIBT24B)

Yes (RIBT24SB)

# **Contact Ratings:**

20 Amp Resistive @ 277 Vac 5 Amp Resistive @ 480 Vac (RIBT24SB) 20 Amp Ballast N/O @ 277 Vac 10 Amp Ballast N/C @ 277 Vac 10 Amp Tungsten N/O @ 120 Vac 1110 VA Pilot Duty @ 277 Vac 770 VA Pilot Duty @ 120 Vac 2 HP @ 277 Vac 1 HP @ 120 Vac

### **Coil Current:**

45 mA @ 18 Vac 75 mA @ 24 Vac 30 mA @ 22 Vdc 32 mA @ 24 Vdc 42 mA @ 30 Vdc

# Coil Voltage Input:

24 Vac/dc; 50-60 Hz Drop Out = 2.1 Vac / 3.8 Vdc Pull  $ln = 18 \, Vac / 22 \, Vdc$ 

#### Notes:

- » Normally Open or Normally Closed selected by yellow jumper wire (RIBT24SB)
- » Order with Momentary Override Switch by adding "-MNO" to end of model number (RIBT24SB)

### Notes